





2 4G LED RGB Controller

F© (€ RoHS





Main Characteristics

V3 RF RGB Remote Control

Remote Option: RGB

Working Voltage: 3Vdc (Battery CR2032)

Wireless Frequency: 2.4GHz

Working Temperature: -30 ~55

Package Size: L150×W46×H18(mm)

Weight(G.W.): 85g

R4-5A CV Receiver

Input Voltage: 5~24Vdc

Max Current Load: 5A × 4CH Max. 20A

Max Output Power: 100W/240W/480W(5V/12V/24V)

Working Temperature: -30 ~55

Package Size: L178×W48×H33(mm)

Weight(G.W.): 150g

R4-CC CC Receiver

Input Voltage: 12~48Vdc Output Voltage: 3~46Vdc

 Output Current:
 CC 350/700/1050mA×4CH

 Output Power:
 1.05W~48.3W×4CH Max 193.2W


Working Temperature: -30 ~55

Package Size: L178×W48×H33(mm)

Weight(G.W.): 165q


Note: Receiver is sold separately.


V3




Dimensions

Unit: mm












Operating Instruction for Remote:



Match/Clear code between remotes

Match code:



Clear code:




Press the bottom two keys of B simultaneously (about 6 seconds), the indicator light keeps on, deactivated matching successfully.

Match/Clear code between remote and receiver


Match code:







Operating Instruction for Receiver:




Clear code:


Long press "ID learning button" on receiver for 5 seconds, If the running light flicker several times, deactivate the matching successfully.

Wiring Diagram:









Attention:

- · Please replace the battery if the remote becomes insensitive or control distance is shortened.
- · Please take out the battery for long time unused.

www.ltech-led.com Update time: 2018 11 19_A2 2